



The leading web-based, Biometric, RFID Smartcard Platform for Enterprise-wide Solutions in ID Management.

ACTAttek Access Manager Lite pre-release version

Last update:2011/09/08

Description:

This is ACTAttek Access Manager Lite version beta release to evaluate and test .We will have full release lite version released with further fixes and additional features support.The below is a simple quick guide to show you how to install and start to evaluate the Access Manager Lite.

Information:

Date: **2011/09/08**

Version:Access Manager Lite v1.0.0 Pre 21 release.

Supports: 10 terminals max. for lite version

Database: Access Manager lite only supports MS SQL Server (including Express version)

OS Support (32bit & 64bit):

XP (32bit only)

Windows vista

Windows 7

Note:MS SQL database is required to install and ready to use before installing ACTAttek Access Manager Lite pre-release version.

Download link:

For ACTAttek2:Access Manager Firmware (2_06.2103)

http://support.hectrix.com/~yongyew/pre-release/actatek2/firmware_2_06.2103.bin

For ACTAttek3:Access Manager Firmware (3_06.1172)

http://www.actatek.com/Downloads/firmware/acta3/firmware_3_06.1172.bin

Note:Please always do the system backup before doing any firmware upgrade.

For Access Manager Lite

64bit OS

http://support.hectrix.com/~terence/AccessManager/AccessManagerLite/Release/AccessManagerLite_1_0_0_21_x64.zip

32bit OS

http://support.hectrix.com/~terence/AccessManager/AccessManagerLite/Release/AccessManagerLite_1_0_0_21_x86.zip

Note:

1.After doing the ACTAttek Firmware upgrade ,and installing the software,you need to set up Access Manager Lite first.See below.



The leading web-based, Biometric, RFID Smartcard Platform for Enterprise-wide Solutions in ID Management.

A.Login to Web Admin page of Access Manager Lite (<http://<IP ADDRESS>:7780/>)

The default login user and password:

user:**admin**

password:1

(Note: IP ADDRESS referred to the PC's IP address where the Access Manager had installed. e.g. <http://192.168.10.20:7780/AccessServer/AccessServices.aspx>)

B.Setup Database connection at:

Control Panel->System Configuration -> Database configuration

Database Type:SQL Server

Database Server Address: e.g. **CHEONG\SQLEXPRESS**

Database Name:any name that is easy to identify

User Name:sa

Password:xxxxx

Click "Setup" which the application will create the Access Manager Lite DB

C.Setup Server :

Control Panel->System Configuration ->Server Setup

Terminal Group:any name that is easy to identify

Time Zone setting:based on the local time zone

Magic String:any digits or characters

P.S Make sure that the "Port :7780" of PC firewall is allowed where the Access Manager Lite is installed.

2.After configuring the software,you will also need to Login to Web Admin page of ACTAttek Terminal,and then go to the "Access Client Setup" by add the below Access manager services end-point URL-->"Set"---->"Register".Wait for the registration process is done.

Access manager service (Sub localhost with IP address and used for ACTAttek Access Client Terminal registration/setup):

<http://<IP ADDRESS>:7780/AccessServer/AccessService.aspx>

(Note: IP ADDRESS referred to the PC's IP where the Access Manager had been installed.e.g.

<http://192.168.10.20:7780/AccessServer/AccessServices.aspx>)

3.After the registration process is done,you can Login to Access Manager Lite to manager the registered ACTAttek Terminals.

Known issues and TODO list:

- 1.Time stamp issue of the report module are not corrected.Bug logged.
- 2.Roll Call Report are not corrected.Bug Logged.

3.View Event Logs-required to add the Employee Photo to compare with Snapshot photo.Bug Logged.

Welcome admin ! [Log Out]

ACTATEK ACCESS MANAGEMENT LITE

Home Access Manager Control Panel About

ACCESS MANAGER

User Depart Group Trigg Event View Termi View Utiliti Repor Dal Det Abi Lat Rol

Event Logs

Selected log

Number of logs: 9297

Terminal Timestamp	UserID	First Name	Last Name	Department	Event	Terminal SN	Terminal Name	Action
2011-01-13 7:04:37 PM	168	Peter		General	IN	00111DA0A122	ACTAtek	Select
2011-01-13 7:04:31 PM	168	Peter		General	OUT	00111DA0A122	ACTAtek	Select
2011-01-12 7:29:10 PM	1112			General	IN	00111DA05586	ACTAtek	Select
2011-01-12 7:29:03 PM	1112			General	IN	00111DA05586	ACTAtek	Select
2011-01-12 5:51:13 PM	1112			General	IN	00111DA05586	ACTAtek	Select
2011-01-12 5:51:04 PM	1112			General	IN	00111DA05586	ACTAtek	Select
2011-01-12 5:49:52 PM	1112			General	IN	00111DA0742C	Eng-SGO	Select
2011-01-12 5:49:33 PM	1112			General	IN	00111DA0742C	Eng-SGO	Select
2011-01-12 5:48:19 PM	1112			General	IN	00111DA05586	ACTAtek	Select
2011-01-12 5:46:51 PM	1112			General	IN	00111DA0742C	Eng-SGO	Select

1 2 3 4 5 6 7 8 9 10 ...

Close

ACTAtek™
WWW.ACTAtek.com

ACTAtek Support Team